

YOUR STEP-BY-STEP GUIDE TO GETTING THE MOST FROM TRIMBLE TECHNOLOGY.

MARCH 2025

## TRIMBLE EARTHWORKS FAQ: TD540 – Select Screen Orientation

Welcome to **SITECH SmartGuide & Go** – your go-to resource for quick, clear, and stepby-step guidance on using Trimble technology with confidence. This series is designed to help you navigate common setup tasks, optimise performance, and get the most out of your equipment—without needing to call support.

In this guide, we'll walk you through **Selecting Screen Orientation on your TD540**, with easy-to-follow instructions to ensure you're up and running in no time.

1. Drag your finger from the very top of screen to reveal the android screen menu.



2. A page will pull down over the home screen. Select settings.

1:33		$\land \land \land \land \land \land$
Fri, 14 Feb * ↔   Φ ① □ ③ ○	File Filoper	String ax
Notifications		
🖁 Machine Control Plugin		
Trimble® Earthworks		
Connected		
Android System		
Configure physical keyboard		
Tap to select language and layout		
MC Installer • 2h		
MC Installer		
All apps are up to date		
Remote.It ScreenView • 2h		
connections service	/556	
Econse Daemon Service + 2h		
License Deemen Service	le.	
	er.	

## 3. Select Display.

	1:34 🕉	ロ I 済・	* ↔
	Add en Let first	nergency information t responders see your information	
	Set Nig Automa	ght Light schedule stically tint screen every night	×
47	<del>?</del>	Network and internet Wi-Fi, data usage and hotspot	
	60	Connected devices Bluetooth, NFC	
		Apps and notifications Recent apps, default apps	
	•	Display Wallpaper, sleep, font size	
	L	Touch Sensitivity	
	4)	Sound Volume, vibration, Do Not Disturb	
		Storage 29% used - 22.84 GB free	
		Permissions, account activity, personal data	



## 4. Select Screen orientation.



5. Now you can select the orientation required. Landscape or Portrait.

1:34 🥉	¤ ⊡ Å •		*↔
÷	Display		Q
	Dark theme On/Will never turn off automatically		
		Screen orientation	
		Candscape	
		O Portrait	
		O Landscape flipped	
		O Portrait flipped	
		CANCEL	
~			
		< • E	



## 6. Select home to exit.

